Docket No.: M&N-IT-558

I hereby certify that this correspondence is being deposited with the United States Postal Service with sufficient postage as first class mail in an envelope addressed to the Commissioner for Patents, P.O. Box 1450, Alexandria, VA 22313-1450, on the date shown below.

By: _____   Date: <u>October 27, 2003</u>

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

Applic. No.	:	10/649,409
Applicant	:	Karl Schrödinger
Filed	:	August 27, 2003
Art Unit	:	to be assigned
Examiner	:	to be assigned

Hon. Commissioner for Patents
Alexandria, VA 22313-1450

SUBMISSION OF DECLARATION AND CERTIFIED ENGLISH TRANSLATION

Sir:

The above-mentioned new patent application was filed on August 27, 2003, without a signed oath or declaration, under the provision of 37 C.F.R. 1.53(f), and in a language other than English.

Applicant herewith submits:

- the original signed declaration in accordance with 37 C.F.R. 1.63(b)
- a certified English translation in accordance with 37 C.F.R. 1.52(d)(1)
- PTO 2038 in the amount of $260.00 to cover the fees for the late filing of the declaration and the English translation.

The undersigned hereby states that the application filed in the Patent and Trademark Office is the application which the inventor executed by signing the declaration. MPEP 602 (8th ed., Aug. 2001).

Please charge any other fees which might be due with respect to Sections 1.16 and 1.17 to Deposit Account No. 12-1099 of Lerner and Greenberg, P.A..

Respectfully submitted,

_____   **Gregory L. Mayback**
For Applicant   **Reg. No. 40,719**
Date: October 27, 2003
Lerner and Greenberg, P.A.
Post Office Box 2480
Hollywood, FL 33022-2480
Tel: (954) 925-1100
Fax: (954) 925-1101
/bb

Docket No.: M&N-IT-558
Application No. 10/649,409

CERTIFICATION

I, the below named translator, hereby declare that: my name and post office address are as stated below; that I am knowledgeable in the English and German languages, and that I believe that the attached text is a true and complete translation of the application filed in German on August 27, 2003, prosecuted under application No. 10/649,409.

I hereby declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under Section 1001 of Title 18 of the United States Code and that such willful false statements may jeopardize the validity of the application or any patent issued thereon.

Hollywood, Florida

Birgit Bartell

October 27, 2003

Lerner & Greenberg, P.A.
P.O. Box 2480
Hollywood, FL 33022-2480
Tel.: (954) 925-1100
Fax.: (954) 925-1101

Description

Receiver circuit

5 <u>Technical field</u>:

The invention relates to a receiver circuit having an optical

reception device and having an amplifier connected downstream

of the optical reception device. Light incident on the optical

reception device - for example light from an optical waveguide

10 of an optical data transmission system - is detected by the

optical reception device with formation of an electrical

signal (e.g. a photocurrent); the electrical signal is

subsequently amplified by the amplifier connected downstream.

15 An optical receiver circuit having an optical reception device

and having an amplifier connected downstream is described for

example in the article "High Gain Transimpedance Amplifier in

InP-Based HBT Technology for the Receiver in 40-Gb/s Optical-

Fiber TDM Links" (Jens Müllrich, Herbert Thurner, Ernst

20 Müllner, Joseph F. Jensen, Senior Member, IEEE,

William E. Stanchina, Member, IEEE, M. Kardos, and

Hans-Martin Rein, Senior Member, IEEE - IEEE Journal of Solid

State Circuits, vol. 35, No. 9, September 2000, pages 1260 to

1265). In the case of this receiver circuit, at the input end

25 there is a differentially operated transimpedance amplifier -

that is to say a differential amplifier - connected by one

input to a photodiode as reception device. The other input of

the differentially operated transimpedance amplifier is

connected to a DC amplifier which feeds a "correction current"

into the differential amplifier for the purpose of offset

5   correction of the photocurrent of the photodiode. The

magnitude of this "correction current" that is fed in amounts

to half the current swing of the photodiode during operation.

Summary of the invention:

10   The invention is based on the object of specifying a receiver

circuit which can be used in particularly universal fashion.

This object is achieved according to the invention by means of

an optical receiver circuit having the features in accordance

15   with patent claim 1. Advantageous refinements of the invention

are specified in subclaims.

Accordingly, the invention provides a receiver circuit having

an optical reception device and an amplifier connected

20   downstream. According to the invention, the amplifier has at

least one control terminal, by means of which the gain of the

amplifier can be changed over at least between two gain values

at the user end.

25   One essential advantage of the receiver circuit according to

the invention is to be seen in the fact that this receiver

circuit enables an optimal optical sensitivity. This is because the invention's adjustability of the gain of the amplifier makes it possible to set the maximum gain of the amplifier depending on the prescribed bandwidth, or bandwidth to be achieved, of the receiver circuit. By way of example, on account of the approximately constant bandwidth (B)-gain (V) product (B * V = K; K results from the individual configuration of the receiver circuit), it is possible to set the maximum gain V and thus the maximum sensitivity of the receiver circuit by choosing

$$V = K \ / \ B.$$

The receiver circuit according to the invention can thus be used optimally for different data rates. Thus, on account of the gain that can be changed over, the receiver circuit according to the invention can be individually adapted for example to transmission rates of 1 Gbps (gigabit per second), 2 Gbps or 4 Gbps.

A further essential advantage of the receiver circuit according to the invention consists in its optimal noise behavior. By way of example, if a photodiode is used as reception device and a transimpedance amplifier is used as amplifier, then the current noise has a particularly relevant part to play in the amplifier. However, the current noise

-3-

generally becomes lower toward higher gains of the amplifier, so that, when the optimum - that is to say maximum - gain is chosen, the current noise of the amplifier also decreases. However, with other types of amplifier, too, it generally

5   holds true that the signal-to-noise ratio becomes better in the case of a higher gain. In summary, an optimum noise behavior can be achieved in the receiver circuit as a result of the user-end setting of the optimum gain value depending on the respective bandwidth requirement.

10

A photodiode is preferably used as the optical reception device since said photodiode can be produced simply and cost-effectively. Transimpedance amplifiers, for example, are particularly suitable as the amplifier.

15

The amplifier preferably has a feedback impedance, which influences the gain of the amplifier. The impedance of the feedback impedance can then be set externally at the user end by means of the at least one control terminal. In particular,

20   the resistance of the feedback impedance should be able to be set at the user end by means of the at least one control terminal.

In order to be able to ensure the adjustability of the

25   impedance of the feedback impedance in a particularly simple manner, one advantageous development of the receiver circuit

-4-

proposes that the feedback impedance is formed by an impedance
network with at least one switching device, which can be
changed over at the user end by means of the at least one
control terminal and which alters the impedance or the
5   resistance of the impedance network in the case of a
changeover.

The switching device is preferably formed by a switching
transistor, in particular a MOS-FET transistor.
10

Another advantageous development of the receiver circuit
proposes that the feedback impedance is formed by an impedance
network with at least one variable impedance, the impedance of
which can be set at the user end within a predetermined
15   impedance range at least approximately linearly by means of
the control terminal. The variable impedance may be formed for
example by a transistor, in particular a MOS-FET transistor.

The receiver circuit is preferably packaged in a TO-46 package
20   or in a corresponding plastic package (e.g. TSSOP10 or
VQFN20).

The invention is furthermore based on the object of specifying
a method for operating an optical receiver circuit in which an
25   optimum noise behavior is achieved depending on the bandwidth
requirements present in the concrete application.

This object is achieved according to the invention by means of a method in which a maximum gain value is prescribed for an amplifier of the receiver circuit in a manner dependent on a prescribed bandwidth of the receiver circuit and the gain

5   value of the amplifier is set by means of a control terminal of the amplifier. The output signal of an optical reception device of the receiver circuit is then amplified by the amplifier with the set gain.

10   With regard to the advantages of the method according to the invention, reference is made to the above explanations concerning the receiver circuit according to the invention.

The gain value (V) of the amplifier may preferably be
15   determined in accordance with

$$V = K \ / \ B,$$

where K specifies a maximum achievable bandwidth-gain product
20   previously determined, for example by measurement, for the receiver circuit and B specifies the prescribed bandwidth.

In transimpedance amplifiers, the bandwidth is approximately proportional to the reciprocal of the feedback impedance, that
25   is to say to 1/feedback impedance, since the gain is proportional to the feedback impedance. In this case, the gain

-6-

is determined by the so-called transimpedance (= output voltage/input current).

5   For elucidating the invention,

figure 1   shows a first exemplary embodiment of a receiver circuit according to the invention, which can also be used to carry out the method according to the

10   invention,

figure 2   shows an exemplary embodiment of a feedback impedance for the optical receiver circuit in accordance with figure 1, and

15

figure 3   shows a further exemplary embodiment of a receiver circuit according to the invention.

Figure 1 reveals a receiver circuit 10 with a photodiode 20 as

20   optical reception device. A transimpedance amplifier 30 is arranged downstream of the photodiode 20. The transimpedance amplifier 30 comprises a voltage amplifier 40, for example an operational amplifier, and a feedback impedance 50. The feedback impedance 50 is connected to the input end of the

25   operational amplifier 40 by its terminal E50 and to the output end of the operational amplifier 40 by its terminal A50.

At the output end, the transimpedance amplifier 30 is additionally connected to a differential amplifier 60, which amplifies the output signal Sa of the transimpedance amplifier 30. Further amplification of the signal is effected by a

5 further differential amplifier 70 arranged downstream of the first differential amplifier 60.

Figure 1 furthermore reveals a control circuit 80, which, at the input end, is connected to the two outputs A70a and A70b

10 of the differential amplifier 70. The control circuit 80 additionally has a control input S80, via which a user-end control signal Sb can be fed into the control circuit 80. The control input S80 thus forms a control terminal S10 of the receiver circuit 10.

15

By an output A80, the control circuit 80 is connected to a control terminal S30 of the transimpedance amplifier 30 and thus to a control input S50 of the feedback impedance 50. Via said control input S50, the control circuit 80 can define the

20 impedance, in particular also the resistance, of the feedback impedance 50 by means of an impedance specification signal Sr formed from the user-end control signal Sb.

Furthermore, the optical receiver circuit is equipped with a

25 DCC circuit 90 (DCC: Duty Cycle Control), which effects a control of the optical receiver circuit. The DCC circuit 90 or

-8-

the duty cycle control formed by it (offset control) controls the sampling threshold for the downstream differential amplifiers, so that the signal is sampled at the 50% value of the amplitude and, as a result, no signal pulse distortions

5   (duty cycle) are produced. This can be effected by feeding a current into a respective one of the preamplifiers (transimpedance amplifiers) or else by feeding in a voltage at the inputs of the differential amplifiers directly.

10 The photodiode 20 is connected via a low-pass filter 100 formed from a capacitor C_{PD} and a resistor R_{PD}, a supply voltage VCC1 being applied to said filter. The low-pass filter 100 serves to "filter out" possible interference signals on the supply voltage VCC.

15

The optical receiver circuit 10 in accordance with figure 1 is operated as follows:

when light is incident, a photocurrent I_{photo} is generated by

20 the photodiode 20 and fed into the transimpedance amplifier 30, where the photocurrent is amplified to form the output signal Sa. The electrical output signal Sa is amplified further by the two differential amplifiers 60 and 70 to form an amplified output signal Sa' and passes to the output A10 of

25 the optical receiver circuit 10; the output A10 of the optical

receiver circuit 10 is thus formed by the two outputs A70a and A70b of the further differential amplifier 70.

The gain of the transimpedance amplifier 30 is set at the user end by means of the control signal Sb via the control terminal S80 of the control circuit 80 or via the control terminal S10 of the receiver circuit 10. For this purpose, the control signal Sb generated at the user end passes to the control circuit 80, which, with its impedance specification signal Sr, sets the resistance of the feedback impedance 50. This is because the magnitude of the resistance ($|R|$) of the feedback impedance 50 directly influences the gain of the transimpedance amplifier 30 because the following holds true:

$$Sa = |R| * I_{photo}$$

thus, in the case of the arrangement in accordance with figure 1, the gain of the transimpedance amplifier 30 can be prescribed at the user end by means of the control signal Sb.

When prescribing an optimum gain value for the transimpedance amplifier 30, it is necessary to take account of the bandwidth B respectively required. In concrete terms, a very large gain is possible given a very small bandwidth, whereas only a very small gain can be achieved given a very large bandwidth. In concrete terms, this is due to the fact that, to a first

approximation, the bandwidth-gain product (V * B) of the
receiver circuit 10 is approximately constant and is
prescribed by the individual configuration of the receiver
circuit. The product V * B can be determined by measurement,
for example.

Thus, if a specific bandwidth is prescribed or is at least to
be achieved, then the maximum permissible gain can be derived
from this at the user end. A corresponding gain value is then
set by the control circuit 80 through the selection of the
corresponding magnitude of the feedback impedance 50.

The desired gain can therefore be prescribed at the user end
via the control input S80 and thus by means of the control
signal Sb. As an alternative - given a corresponding
configuration of the control circuit 80 - a bandwidth to be
achieved can also be communicated to the control circuit 80 at
the user end by means of the control signal Sb, from which the
maximum permissible gain V is then determined by the control
circuit 80 in accordance with the mathematical relationship
mentioned above and is communicated to the transimpedance
amplifier 30 via the output A80 and the control terminal S50.

In connection with figure 1, the user-end control signal Sb
was conducted to the transimpedance amplifier 30 via the
control device 80. Instead of this, the user-end control

signal Sb may also be applied directly to the control terminal S30 of the transimpedance amplifier 30.

Moreover, the transimpedance amplifier 30, the two differential amplifiers 60 and 70, the control circuit 80 and the DCC circuit 90 may also be regarded as one "amplifier unit" or as one "amplifier" whose control terminal for feeding in the user-end control signal Sb is formed by the terminal S80 of the control circuit 80.

Figure 2 illustrates an exemplary embodiment of a feedback impedance 50 in accordance with figure 1. The feedback impedance is formed by an impedance network. The illustration reveals an ohmic resistor RF1, with which three capacitors CF1, CF2, CF3, CFC1 and CFC2 are connected in parallel. In addition, further ohmic resistors RF2 and RF3 are connected in parallel with the resistor RF1.

As can be discerned in figure 2, the resistor RF2 and the capacitor CF2 are connected in parallel and are connected to a switching transistor 210. If the switching transistor 210 is switched off, then the resistor RF2 and the capacitor CF2 play no part in the total impedance of the impedance network. By contrast, if the switching transistor 210 is switched on, then the resistors RF1 and RF2 form an ohmic parallel connection, with the result that the total resistance of the impedance

-12-

network is reduced. The capacitor CF2 correspondingly

increases the total capacitance of the impedance network since

the capacitor CF2 is added to the capacitor CF1.

5   The resistor RF3 and the capacitor CF3 can be connected in

parallel with the first resistor RF1 in a corresponding manner

by means of a second switching transistor 220.

Figure 2 furthermore reveals a MOS-FET transistor 230, which

10   represents a linearly controllable resistor. Depending on the

gate voltage applied to the MOS-FET transistor, a transistor

resistor is produced which is connected in parallel with the

first resistor RF1 and thus linearly reduces the total

resistance of the impedance network. The resistance of the

15   impedance network can be set in a continuously variable manner

by application of the gate voltage.

Via a third switching transistor 240 and a fourth switching

transistor 250, the capacitor CFC1 and the capacitor CFC2 can

20   likewise be connected in parallel with the first resistor RF1,

or else "disconnected".

Figure 2 furthermore reveals a coding device 300, the input

E300 of which forms the control terminal S50 of the feedback

25   impedance 50 in accordance with figure 1. At the output end,

the coding device 300 is connected to the four switching

-13-

transistors 210, 220, 240 and 250 and also to the linearly operating MOS-FET transistor 230.

The coding device 300 serves to recode the impedance specification signal Sr formed by the control circuit 80 in such a way that the feedback impedance 50 or the impedance network forms the desired impedance and the transimpedance amplifier 30 thus achieves the required gain.

The impedance network is driven as follows for the operation of the receiver circuit in accordance with figure 1:

The resistor RF1 serves for setting the largest gain and thus the smallest bandwidth of the transimpedance amplifier 30. In this operating mode - that is to say with the smallest bandwidth - the second resistor RF2 and the third resistor RF3 are disconnected by the two switching transistors 210 and 220. The capacitor CF1 serves for compensation against oscillation tendencies of the receiver circuit 10.

If a higher data rate is required, then the second resistor RF2 is connected in, by way of example; a lower transimpedance impedance is thus produced as a result of the two resistors RF1 and RF2 being connected in parallel, as a result of which the gain of the transimpedance amplifier 30 is reduced and the bandwidth is increased.

-14-

As a result of further connection - for example of the third resistor RF3 - the resistance of the feedback impedance 50 and thus the gain of the transimpedance amplifier 30 can be reduced further, as a result of which the bandwidth is

5   increased further. The compensation capacitors CF2 and CF3 that are necessary, if appropriate, for compensation against oscillation tendencies are additionally connected in at the same time as the two resistors RF2 and RF3 by the two switching transistors 210 and 220. In this case, the

10   transistors 210, 220, 230, 240 and 250 are changed over by the control signal SV by means of the coding device 300.

The function of the MOS-FET transistor 230, which is likewise controlled by the coding device 300 and the control circuit

15   80, serves primarily for amplitude control. If the output power of the transimpedance amplifier rises increasingly, then the transistor 230 is driven linearly, so that the feedback impedance (transimpedance impedance) 50 of the transimpedance amplifier 30 is continuously decreased: overdriving of the

20   transimpedance amplifier 30 can be prevented in this way. In order to be able to identify an increase in the output power of the transimpedance amplifier 30, the control circuit 80 in accordance with figure 1 is connected to the output signals Sa' and -Sa' of the further differential amplifier 70.

25

-15-

The additional capacitors CFC1 and CFC2 can be connected in
with the associated switching transistors 240 and 250 in order
to avoid oscillations; this may be necessary particularly when
the feedback impedance 50 of the transimpedance amplifier 30
5   is decreased linearly on account of the MOS-FET transistor
230.

In summary, in the case of the exemplary embodiment in
accordance with figure 2, the feedback impedance 50 is reduced
10   by resistors and/or capacitors being connected in "parallel".
Instead of this or in addition, a changeover of the impedance
of the feedback impedance 50 may also be achieved through a
series circuit of connectable resistors and/or connectable
capacitors.

15

The coding device 300 may be formed for example by an
integrated circuit which correspondingly converts the
impedance specification signal Sr in such a way that the
transistors 210, 220, 230, 240 and 250 are driven in the
20   manner explained above.

Figure 3 illustrates a second exemplary embodiment of an
optical receiver circuit 10 according to the invention. The
optical receiver circuit in accordance with figure 3 differs
25   from the receiver circuit in accordance with figure 1 by
virtue of an additional receiver path 400 connected upstream

-16-

of the differential amplifier 60. The additional receiver path

400 has a "dummy" photodiode 410, which is connected to the

low-pass filter 100 and thus to the supply voltage VCC1. The

"dummy" photodiode 410 is connected to a transimpedance

5   amplifier 420, which, at the output end, is connected to a

further input of the differential amplifier 60.

The function of the "dummy" photodiode 410 is to simulate the

electrical behavior of the photodiode 10, to be precise for an

10   "illumination-free case". An "illumination-free case" is

understood here to mean that the "dummy" photodiode 410

behaves to the greatest possible extent just like the

photodiode 10 if no light to be detected impinges on the

photodiode. In order to prevent light from being able to

15   impinge on the "dummy" photodiode 410, the latter is

correspondingly darkened, which is illustrated by a bar in

figure 3.

One advantage of the receiver circuit in accordance with

20   figure 3 is that it has a "fully differential" design or a

quasi-symmetrical input-end circuitry of the differential

amplifier 60. In this case, the fully differential design is

based on the "dummy" photodiode 410 which simulates the

electrical behavior of the photodiode 10 in the illumination-

25   free case. The differential amplifier 60 is connected up

symmetrically on account of the "dummy" photodiode 410, so

-17-

that high-frequency interference is effectively suppressed.
This is because high-frequency interference will occur
simultaneously on account of the symmetrical input-end
circuitry of the differential amplifier 60 at the two inputs

5   E60a and E60b of the differential amplifier 60, so that the
interference is suppressed to the greatest possible extent by
virtue of the common-mode rejection that is customarily high
in the case of the differential amplifier 60.

10   The optical receiver circuit in accordance with figure 3 is
thus a development of the receiver circuit described in figure
1 which, although it has a differential amplifier at the input
end, is connected up asymmetrically at the input end.
Potential interference elements such as the bonding wire of

15   the photodiode 10, the capacitance of the photodiode 10 and
further capacitive construction elements - for example
capacitances and inductances in the region of the photodiode
10 - are unimportant in the arrangement in accordance with
figure 3 since their influence or their interference signals

20   are suppressed by the differential amplifier 60. This is based
in concrete terms on the fact that the interference signals
going back to the photodiode 10 are formed in a corresponding
manner by the "dummy" photodiode 410 and thus pass "in common
mode" to the differential amplifier 60 and are suppressed

25   there.

In order to enable fully symmetrical operation of the optical

receiver circuit in accordance with figure 3, at the output

end the control circuit 90 is connected by its output A80 both

to the feedback impedance 50 of the transimpedance amplifier

5   30 and to a feedback impedance 430 of the transimpedance

amplifier 420, which likewise has an operational amplifier

440, so that the two feedback impedances 50 and 430 are driven

in the same way.

10   The two transimpedance amplifiers 30 and 420 thus have the

same gain behavior, so that "fully symmetrical" operation of

the differential amplifier 60 is made possible because the

receiver path formed by the photodiode 10 and the additional

receiver path 400 formed by the "dummy" photodiode 410 are in

15   parallel.

With regard to the remaining properties of the receiver

circuit in accordance with figure 3, reference is made to the

above explanations in connection with figure 1. By way of

20   example, the impedance network in accordance with figure 2 may

be used as feedback impedance 50 and as feedback impedance

430.

Figure 3 furthermore reveals terminal pads 500 and 510, which

25   can be connected to one another by means of a bonding wire

520. By means of such a bonding wire 520, the capacitor C_{SYM}

-19-

can be connected to the further transimpedance amplifier 420. In this case, the capacitor C_{SYM} may replace the "dummy" photodiode 410 if such a photodiode 410 is not available. The capacitor C_{SYM} is then preferably dimensioned in such a way that it essentially corresponds to the capacitance of the "absent" dummy photodiode 410 or the capacitance of the useful diode 10.

List of reference symbols

	10	Receiver circuit
	20	Photodiode
5	30	Transimpedance amplifier
	40	Operational amplifier
	50	Feedback impedance (transimpedance impedance)
	60	Differential amplifier
	70	Further differential amplifier
10	80	Control circuit
	90	DCC circuit
	100	Low-pass filter
	200/210	Switching transistor
	220	Switching transistor
15	230	Linearly controllable MOS-FET transistor
	240	Switching transistor
	250	Switching transistor
	300	Coding device
	400	Additional receiver path
20	410	"Dummy" photodiode
	420	Second transimpedance amplifier
	500	Terminal pad
	510	Terminal pad
	520	Bonding wire
25	Sr	Impedance specification signal
	Sb	User-end control signal

Patent Claims

1. A receiver circuit (10)

    -   having an optical reception device (20) and

    - having an amplifier (30) connected to the reception

    device (20),

    - the amplifier (30) having at least one control

    terminal (S30), by means of which the gain (V) of the

    amplifier (30) can be changed over at least between

    two gain values at the user end.

2. The receiver circuit as claimed in claim 1, characterized
in that the amplifier is a transimpedance amplifier (30).

3. The receiver circuit as claimed in one of the preceding
claims, characterized in that the amplifier (30) has a
feedback impedance (50), which influences the gain (V) of the
amplifier (30).

4. The receiver circuit as claimed in one of the preceding
claims, characterized in that the impedance of the feedback
impedance (50) can be set at the user end by means of the at
least one control terminal (S30).

5.   The receiver circuit as claimed in claim 4, characterized in that the resistance of the feedback impedance (50) can be set at the user end by means of the control terminal (S30).

6.   The receiver circuit as claimed in one of the preceding claims, characterized in that the feedback impedance (50) is formed by an impedance network with at least one switching device (210, 220, 230, 240, 250), which can be changed over at the user end by means of the at least one control terminal (S30) and which alters the impedance of the feedback impedance (50) in the event of changeover.

7.   The receiver circuit as claimed in claim 6, characterized in that the switching device is formed by a switching transistor.

8.   The receiver circuit as claimed in claim 7, characterized in that the switching transistor is a MOS-FET transistor or a bipolar transistor.

9.   The receiver circuit as claimed in one of the preceding claims, characterized in that the feedback impedance (50) is formed by an impedance network with at least one variable impedance, the impedance of which can be set within a predetermined impedance range at least approximately linearly at the user end by means of the control terminal (S30).

-23-

10. The receiver circuit as claimed in claim 9, characterized in that the variable impedance is formed by a transistor (230).

11. The receiver circuit as claimed in claim 10, characterized in that the variable impedance is formed by a MOS-FET transistor or a bipolar transistor.

12. The receiver circuit as claimed in one of the preceding claims, characterized in that the reception device is a photodiode (20).

13. The receiver circuit as claimed in one of the preceding claims, characterized in that the receiver circuit is packaged in a TO-46 package, a TSSOP10 package or a VQFN20 package.

14. The receiver circuit as claimed in claim 13, characterized in that the at least one control terminal (S30) is formed by a terminal pin of the package.

15. A method for operating an optical receiver circuit, in which

- a gain value is prescribed for an amplifier of the receiver circuit in a manner dependent on a bandwidth prescribed for the receiver circuit (10),

- the gain value of the amplifier is set at a control
terminal (S30) of the amplifier (30), and
- the output signal of an optical reception device
(20) of the receiver circuit is amplified by the
previously set amplifier.

16. The method as claimed in claim 15, characterized in that
the gain value (V) is determined in accordance with

$$V = K / B,$$

where K specifies a maximum achievable bandwidth-gain product
previously determined for the receiver circuit and B denotes
the prescribed bandwidth.

Abstract

Receiver circuit

5   The invention is based on the object of specifying a receiver

circuit which can be used in particularly universal fashion.

This object is achieved according to the invention by means of

a receiver circuit (10) having an optical reception device

10   (20) and having an amplifier (30) connected to the reception

device (20), the amplifier (30) having at least one control

terminal (S30), by means of which the gain (V) of the

amplifier (30) can be changed over at least between two gain

values at the user end.

15

20   Figure 1